

To be read in full before installation
and kept for future reference

Operating Instructions USB Charging Socket Outlets

S1298	Slimline
1998CHW	Decorative Chrome with white inserts
1998CHB	Decorative Chrome with white inserts
1998SCW	Decorative Satin Chrome with white inserts
1998SCB	Decorative Satin Chrome with white inserts

Safety Instructions

- Always switch off the electrical supply before commencing installation.
- Connect to a 240V ac electrical supply.
- This socket and metal back boxes must be earthed.
- Only suitable for indoor use.
- Note: The front surface of this product may become warm in use.
- The USB ports are for charging information technology equipment only.
- This socket must be installed in accordance with the current edition of the IEE Wiring Regulations and Building Regulations, BS 7671.

If in doubt, contact a qualified electrician

Product Features

13A DP Switched Socket complete with 2 USB Charging Ports

- This USB Charger is compatible with portable devices such as smart phones, tablets and other such devices that require charging via a USB 2.0 type A port.
- The USB charging ports are configured and optimized to charge tablets from the 'Tablet' port and phones from the 'Phone' port.
- The USB Charger is capable of simultaneously providing 2.4A via the 'Tablet' port and 1A via the 'Phone' port.
- Fits Deta 35mm flush and dry lining boxes. Slimline version comes complete with 10mm spacer for mounting into 25mm boxes

Specification

USB Output (total)	3.4A at 5V	Voltage	240V ac 50Hz
'Phone' Port Output	1.0A at 5V	13A Socket Current Rating	13A
'Tablet' Port Output	2.4A at 5V	Compliance	BS 1363:Pt 2

NPD 0411 02/2015 V2



Deta Electrical Company Limited

Kingsway House Laporte Way

Luton Bedfordshire LU4 8RJ UK

Tel.: +44 (0)1582 544 544 Technical Helpline: +44 (0)1582 544 548