


Dimmer Switches



Description

This range of dimmers within the Deta Flatplate range can control mains voltage and low voltage lamps.

Our LED versions are designed specifically with LED lighting in mind and are optimised to control our dimmable LED Fire Rated Downlights, as well as other leading brands of LED lamps, with minimal programming.

Features

- LED and incandescent / LV lamp versions available
- Push on / push off control suitable for 2W circuits
- LED versions can be 2-way controlled using push-to-make switches
- Clear white terminal markings
- 2-year guarantee

Range

| | |
|---------------------------|------|
| 1g 2w 60-400W push on/off | 8121 |
| 2g 2w 60-400W push on/off | 8122 |
| 1g 2w 100W push on/off | 8125 |
| 2g 2w 100W push on/off | 8126 |

Technical Specification

Voltage rating 250Vac
Frequency 50Hz

LED dimmers

- LED – 100W
- Mains voltage
- halogen – 200W
- Incandescent and ECO halogen – 250W

Incandescent dimmers 60-400W

No user serviceable parts

Back Boxes

Minimum recommended depth

| | Flush 35mm | Dry Lining 35mm |
|-------|---------------|--------------------|
| 1g/2g | DB164 | DB2547 |

Standards

- BS EN 60669-2-1

Terminal Capacity

| | 1mm ² | 1.5mm ² |
|---|------------------|--------------------|
| L | 2 | 2 |