


## Dimmer Switches



### Description

This range of dimmers within the Deta Vimark range can control mains voltage and low voltage lamps.

Our LED versions are designed specifically with LED lighting in mind and are optimised to control our dimmable LED Fire Rated Downlights, as well as other leading brands of LED lamps, with minimal programming.

### Features

- LED and incandescent / LV lamp versions available
- Push on / push off control suitable for 2W circuits
- LED versions can be 2-way controlled using push-to-make switches
- Terminals have clearly embossed and white printed markings
- 2-year guarantee

### Range

#### LED Dimmer

1g 2w 100W push on/off	V1255
2g 2w 100W push on/off	V1256

#### Standard Dimmer

1g 2w 60-400W push on/off	V1253
2g 2w 60-400W push on/off	V1254

### Technical Specification

Voltage rating	250Vac
Frequency	50Hz

LED dimmers	<ul style="list-style-type: none"> <li>• LED – 100W</li> <li>• Mains voltage</li> <li>• halogen – 200W</li> <li>• Incandescent and ECO halogen – 250W</li> </ul>
Incandescent dimmers	60-400W

No user serviceable parts

### Standards

- BS EN 60669-2-1

### Back Boxes

Minimum recommended depth

	Flush 25mm	Dry Lining 35mm	Surface 25mm
1g/2g	DB162	DB2540	V1221

### Terminal Capacity

	1mm <sup>2</sup>	1.5mm <sup>2</sup>
L	2	2